



## RL7327 80VA 12V

80W 12V

Quicklink: Q41A9

### General

Construction Plastic

Dimmable Yes

### Dimensions

Transformer Height 32mm

Transformer Length 111mm

Transformer Width 58mm

### Electrical

Maximum Wattage 80W

Minimum Wattage 20W

Voltage 12V

Makes any table, floor or desk lamp into a touch lamp, if it is wired anywhere into the mains flex, and the bulbs are 12V with the unit providing the transformer facility to 12V as well Push-button or sensorial control .

**Please Note** If there is a separate transformer in the light this will not work. The lamp must take dimmable bulbs between 20 and 80W (normal low energy cfls must not be used in touch lamps).

## Features

- Continuous sensorial regulation
- Push-button or sensorial control (5501 PSC)
- Mains polarity independent sensor
- Distance between circuit and sensor: < 2 m
- Light intensity memory also without mains
- Amperometric protection (non resetting fuse resistance)
- Protection against transient surges
- Overload and short-circuit protection
- Soft-Start
- Soft-Stop
- Switch-on from wall socket