

Indicator

LED Emergency 700mA
3W 60°



MR. RESISTOR[®]
Lighting Specialist Est. 1968



LDCK700/38/LDE3

3W 60°
Quicklink: Q2842

The **LED Emergency** downlight is non-maintained meaning that it only becomes illuminated when there is a power cut; its normal state is off with the 1mm green healthy battery indicator lit. In the event of a power cut the supplied sausage battery pack becomes active and powers the 3 Watt LED for up to 3 hours.

Emergency downlights are traditionally fitted in corridors and near fire exits to allow safe evacuation of buildings in the event of a power outage.

General

Colour White
Construction Aluminium

Battery 3 hrs
Emergency Type Non-maintained

Dimensions

Cut Out 45mm (Diameter)
Diameter 56mm
Pack Diameter 35mm
Pack Length 300mm

Electrical

Amperage 700mA
Maximum Wattage 3W

Light Characteristics

Beam Angle 60°
Colour Temperature 4000K Cool White
Lumens 100 lm
Lumens Per Watt 33 lm/W