

Emergency Pierrot

Pierrot Square 350mA Emergency Kit
4000K Cool White 1W



AL4020 C/W EMERGENCY

4000K Cool White 1W
Quicklink: Q2861

General

Colour	White
Construction	Aluminium

Battery	3 hrs
Emergency Type	Maintained

Dimensions

Battery Depth	90mm
Battery Length	150mm
Battery Width	100mm
Depth	75mm
Length	70mm
Pack Depth	190mm
Pack Length	400mm
Pack Width	300mm
Width	70mm

Electrical

Amperage	350mA
Maximum Wattage	1W

Light Characteristics

Colour Temperature 4000K Cool White

The **Pierrot Square Emergency Kit** is a 1W low level light with a Distributed Power Supply Unit and Wise Converter.

The **Distributed Power Supply Unit** provides maintained operation of 12 x 3W LED light pods and drivers or 20 x 1W light pods and drivers with a 3hour duration emergency lighting back-up.

Please note: We would recommend that a maximum of 18 Pierrot Square 1W fittings be connected to this unit.

Also included with this Emergency Pack is **The Wise Converter** which is a power supplier for 1W or 3W LEDs with a built in constant current regulator. Starting from a direct power supply the product allows to supply a series of 350mA d.c LEDs. One Wise Converter is required for each Pierrot Square fitting. Emergency packs are used in commercial buildings as a safety precaution to power outages, so that people will be able to find their way out of a building in the event of an emergency.

Maintained Emergency Lighting: The emergency light units are illuminated at all times using the same lamps for both normal and emergency operation. Please note maintained fittings can be wired as non-maintained.

Non-Maintained Emergency Lighting: A non maintained fitting is not illuminated until the event of power failure.

Emergency lights are traditionally fitted in corridors and near fire exits to allow safe evacuation of buildings in the event of a power outage.

Emergency Pierrot

Pierrot Square 350mA Emergency Kit
4000K Cool White 1W

