

Wise Fusion Smart LED Dimmer Slave Wireless

Wise Fusion Smart Dimmer Slave Wireless 2 Gang
Walnut 3V



MR. RESISTOR[®]
Lighting Specialist Est. 1968



WISE FUSION2 WALNUT

Walnut 3V
Quicklink: Q2DFB

General

Colour Walnut
Construction Wood / Plastic
IP Rating IP20

Maximum Switches per Receiver 16
Operating Temperature -10°C ~ +55°C
Radio Frequency 868.3 MHz
Receiver Range 50m

Dimensions

Depth 9mm
Height 86mm
Width 86mm

Electrical

Replacement Battery CR2430
Voltage 3V

The **Wise Fusion Smart Dimmer Slave** is a dimmer based around wireless communication technology that talks to a corresponding **Wise Fusion Dimmer Master**. They are surface mounted and battery powered so can be positioned almost anywhere. A CR2430 battery is included with each unit.

This dimming unit has 6 simple buttons to control two lighting circuits: on/off, raise and lower.

What makes these dimmers distinct is the wireless communication between a receiver unit and transmitter unit. A **Wise Fusion Dimmer Master** is designed to replace your existing light switch using the existing cables. It can then be synched to a number of **Wise Fusion Dimmer Slaves** that are completely wireless and can simply be placed around your house. No more chasing wires through wall cavities. You now have the freedom to put your lighting dimmer wherever you want and if you don't like the position, you can easily move it.

This *Wise Fusion Dimmer Slave - 2 Gang* is compatible with four different programming options:

Option A - Single Button Dimming Programming

Allows circuits to be switched ON/OFF or dimmed from a single button.

Option B - Switching ON only Programming

Allows you to switch single or multiple circuits ON. Ideal for programming a 'Master On' switch to turn on certain circuits as you enter your home.

Option C - Switching OFF only Programming

Allows you to switch single or multiple circuits OFF. Ideal for programming a 'Master Off' button for your home.

Option D - Three Button Dimming Programming

Allows circuits to be switched ON/OFF, raise or lower using a three button switch.

The battery life lasts up to five years.