

In-Line Touch/Push Dimmer

In Line Touch/Push Dimmer
80W 12V



RL7327 80VA 12V

80W 12V

Quicklink: Q41A9

General

Construction Plastic

Dimmable Yes

Dimensions

Transformer Height 32mm

Transformer Length 111mm

Transformer Width 58mm

Electrical

Maximum Wattage 80W

Minimum Wattage 20W

Voltage 12V

Makes any table, floor or desk lamp into a touch lamp, if it is wired anywhere into the mains flex, and the bulbs are 12V with the unit providing the transformer facility to 12V as well Push-button or sensorial control .

Please Note If there is a separate transformer in the light this will not work. The lamp must take dimmable bulbs between 20 and 80W (normal low energy cfls must not be used in touch lamps).

Features

- Continuous sensorial regulation
 - Push-button or sensorial control (5501 PSC)
 - Mains polarity independent sensor
 - Distance between circuit and sensor: < 2 m
 - Light intensity memory also without mains
 - Amperometric protection (non resetting fuse resistance)
 - Protection against transient surges
 - Overload and short-circuit protection
 - Soft-Start
 - Soft-Stop
 - Switch-on from wall socket
-