

Pierrot

Pierrot Square 350mA

1W Blue



AL4020 BLUE

1W Blue

Quicklink: Q1B00

General

Colour	White
Construction	Aluminium
Dimmable	Yes
IP Rating	IP65

Dimmable Yes

Dimensions

Burial Tube Cut Out	62mm
Cut Out	53mm (Diameter)
Depth	32mm
Depth	33mm
Length	70mm
Plate Depth	2mm
Tube Length	72mm
Width	70mm

Electrical

Amperage	350mA
Maximum Wattage	1W

The **Pierrot Square** is a 1W, 350mA LED wall fitting that is used to light floors. It is ideally used to highlight walkways such as paths or corridors and due to its IP65 rating, can be used in bathrooms or outside.

The fitting has a 50,000 hour life which means that maintenance such as lamp changing is now officially a thing of the past. A burial tube is included for easy installation into a wall.

Many different LED power supplies are available that allow you to achieve more with your lighting. Simply select the correct wattage depending on how many total LED fittings it will be connected to.

LED Driver Options

- LED Driver (Switching) - Use this driver for on/off control. Cannot be used for dimming.
- LED Driver (Dimming) - For use with nearly all domestic dimming lighting. Most resistive dimmers have a minimum load of 60W, therefore ensure that if this not met, a dummy load is added to the circuit, such as a mains voltage halogen fitting.
- LED Driver (1-10V) - For use with 1-10V dimmer modules or 1-10V control systems. This type of dimming does not have a minimum load.
- Wise Chameleon (Dimming + Wireless) - This controller can be used for both switching and dimming. Additionally, this unit can communicate via radio and external push buttons, allowing you to wirelessly control your fitting. Note that an additional 24V LED driver is required to power the Wise Chameleon pack.
- DMX (Dimming + Channel Control) - This transformer can be used for both switching and dimming as well as being fully addressable and compatible with the DMX control standard.

Pierrot

Pierrot Square 350mA
1W Blue

