

Rock 'n' Roll

Rock 'n' Roll 50 Emergency

Brass 50W



DL336/EMERGENCY BRASS

Brass 50W

Quicklink: Q2226

General

Cap	GU5.3 / MR16
Colour	Brass
Construction	Die-Cast Aluminium
IP Rating	IP20

Battery	3 hrs
Emergency Type	Maintained/Non Maintained

Dimensions

Cut Out	80mm (Diameter)
Diameter	90mm
Horizontal Rotation	360°
Minimum Ceiling	68mm
Depth	
Pack Diameter	60mm
Pack Length	600mm
Vertical Rotation	35°

Electrical

Maximum Wattage	50W
Voltage	12V

The **Rock 'n' Roll 50** is a fully adjustable 50mm downlight. The inner ring can tilt to a maximum of 35° for precise beam placement. Included with this product is the **Slimline Emergency Conversion 12V 50W 3hr**.

The outer ring of this product is permanently attached to the ceiling and the two inner rings are one piece. These two inner rings are easily pulled out to reveal the lampholder. This simply pushes back in place afterwards. No clips or tools are needed, simplifying the lamp replacement process without compromising the design.

The **Slimline Emergency Conversion 12V 50W 3hr** is used for maintained or non-maintained operation for use with a maximum of 50watt lamps at 6volts for 3hours. This unit is supplied with a integral 12V maintaining transformer.

Emergency packs are used in commercial buildings as a safety precaution to power outages, so that people will be able to find their way out of a building in the event of an emergency.

Maintained Emergency Lighting: The emergency light units are illuminated at all times using the same lamps for both normal and emergency operation. Please note maintained fittings can be wired as non-maintained.

Non-Maintained Emergency Lighting: A non maintained fitting is not illuminated until the event of power failure.
