



Wise Fusion Smart LED Dimmer Master Wired

Wise Fusion Smart Dimmer Master Wired 2 Gang 240V
Satin White Aluminium 2 x 250W



MR. RESISTOR[®]
Lighting Specialist Est. 1968



WISE FUSIONREC2W ALU.WHT

Satin White Aluminium 2 x 250W
Quicklink: Q2D3D

General

Colour	Satin White
Construction	Steel / Plastic
IP Rating	IP20

Maximum Scenes per 64
Receiver

Maximum Switches 16
per Receiver

Operating -10°C ~ +55°C
Temperature

Radio Frequency 868.3 MHz

Range for Metal 50m Max Line Of
Switch Sight

Range for Plastic 100m Max Line Of
Switch Sight

Dimensions

Depth 25mm

Height 86mm

Plate Depth 9mm

Width 86mm

Electrical

Input Voltage 240V

Maximum Wattage 500W (2 x 250W)

Minimum Wattage 50W

Minimum Wattage 2x25

Breakdown

Output Voltage 240V

Our **Wise Fusion Smart Dimmer Master** is a retro dimmer based around two technologies: electronic dimming and wireless communication.

This dimming unit has six simple buttons to control two lighting circuits: on/off, raise and lower.

What makes these dimmers distinct is the wireless communication between a receiver unit and transmitter unit. It is designed to replace your existing light switch using the existing cables. It can then be synched to a number of *Wise Fusion Dimmer Slaves* that are completely wireless and can simply be placed around your house. No more chasing wires through wall cavities. You now have the freedom to put your lighting dimmer wherever you want and if you don't like the position, you can easily move it.

On top of this, the *Wise Fusion Range* offers you a number of options for both simple and more complex lighting control. For simple 2 way dimming a *Wise Fusion Dimmer Slave - 1 Gang* is used. For more elaborate scene control a *Wise Fusion Dimmer Slave - 7 Channel* dimmer can be employed. A single button in this case can be programmed as a master ON or OFF.

PLEASE NOTE: Circuit with highest load needs to be wired to channel 1 and must be 25W minimum.

Five different options can be programmed using our wireless *Wise Fusion Dimmer Slaves*:

Option A - Scene Programming

Programming a 7 button switch gives you 4 scenes, master raise/lower and off. It gives you the flexibility to create different atmospheres in your house, controlling multiple circuits on one button. You can store different scenes on different *Wise switches*. Allows up to 64 scenes. For example, you can have 4 *Wise Fusion Dimmer Masters* (4 gang) in your living room. Pressing scene 1 on the 7 button switch could give the following;

Downlights = 100%

Wall lights = 80%

Pendant = Off

Low level LEDs = 55%

Pressing scenes 2,3 and 4 can give other preset levels. Any level can be programmed to each receiver.

Option B - Single Button Dimming Programming

Allows circuits to be switched ON/OFF or dimmed from a single button.



Option C - Switching ON only Programming

Allows you to switch single or multiple circuits ON. Ideal for programming a 'Master On' switch to turn on certain circuits as you enter your home.

Option D - Switching OFF only Programming

Allows you to switch single or multiple circuits OFF. Ideal for programming a 'Master Off' button for your home.

Option E - Three Button Dimming Programming

Allows circuits to be switched ON/OFF, raise or lower using a three button switch.

A receiver is not limited to one of the programming options. E.g. you can program a switch for scene control, another switch for dimming and another switch for master ON/OFF.

Wireless Switches and Remotes

Although the Wise Fusion Slave has been designed specifically for this product, other Wise switches, remotes and keyfobs are all compatible and offer the same functionality. A 7 button switch or remote must be used if you require scene setting, Option A. Any switch or remote can be used when programming options B, C, D and E. A one button keyfob is sufficient for options B, C and D. To view other types and finish colours, click the links on the right of this page.

Wise Fusion Programming

