

# Switching On/Off

Wise Box 2 Channel Kit includes Keyfob & Keypad  
2 Channel 2 x 1000W

---



## WISEBOX 2CH KIT

2 Channel 2 x 1000W  
Quicklink: Q2E9D

---

### General

IP Rating IP54

Detection Range 200m

### Dimensions

Depth 80mm

Height 184mm

Width 200mm

### Electrical

Amperage 20A

Maximum Amps /  
Circuit 10A

Minimum Wattage  
per Circuit 1W

Voltage 240V

The **Wise Time Lag Box Kit** is a receiver that has three functions. The functions are on/off switching, push-to-make switching and timelag switching. The timelag function can be set to work between 1 second and 9 hours. This is very popular when installing lighting for communal hall ways and stair cases. As the switches are all wireless they can be placed anywhere with minimal effort.

The receiver has two 10 amp channels with a 200 metre range. These channels can be changed from switching to push-to-make. Each circuit on the box is fused individually with a 10 amp fuse to protect all the circuits.

It can be programmed in 4 different ways:

#### Option A - Push-to-make

The circuit will work as push-to-make from a single button.

#### Option B - Single Button Switching ON/OFF

The circuit can be turned ON/OFF from a single button.

#### Option C - Two Button Switching ON/OFF

The circuit can be turned ON/OFF from two buttons, for independent ON and OFF.

#### Option D - Time Delay

The circuit can have a timer on it. Use a single button to turn the lights on. The timer will turn the circuit off after the set time has passed. Use a two button switch for control. To turn on, press button 1 and either wait for the delay time or press button 2 to turn off.

## Wise Controls Introduction Video

