



The **Wise Rail RGBW DMX/DALI Interface** brings Wise Controllers together. You can now control the Wise Chameleon from either your DMX/DALI control system or your Wise wireless switches, giving you the benefits of both DMX/DALI wired and Wise wireless controlling.

If the input voltage is 12V then the maximum wattage will be 150W as the Wise Rail is 37.5W per channel. If the input wattage is 24V then the maximum wattage will be 300W as the Wise Rail is 75W per channel.

WISERAIL RGBW

RGBW DMX/DALI 300W
Quicklink: Q4387

General

Construction Plastic

Radio Frequency 868.3 MHz

Dimensions

Depth 58mm

Height 90mm

Width 88mm

Electrical

Input Voltage 12V / 24V

Maximum Wattage 300W