



## HTI DALI 315 DIM

315W

Quicklink: Q480C

The **Dali to Phase Interface** is used to convert any dali signal to a trailing edge dimmer. This means that you can connect mains 240V pendants, LED GU10s and other 240V lighting that does not have the DALI input.

### Product features:

- DALI trailing-edge phase dimmer
- Dimming of high voltage halogen and incandescent lamps
- Dimming of many common dimmable line voltage LED lamps
- Dimming of electronic transformers
- Standby power consumption: < 0.5 W
- DALI/Touch DIM control signal
- Short-circuit protection, overload protection, over temperature protection: electronically reversible
- RI suppression: to EN 55015 (A1: 2007)
- Line harmonics according to EN 61000-3-2
- Safety: to EN 61347
- Immunity according to EN 61547
- Device fits also for special applications where dimming below 1 % is required

### General

Colour	White
Construction	Plastic
Dimmable	Yes
IP Rating	IP20

Dimmable	Yes
Operating Temperature	45°C

### Dimensions

Height	36mm
Length	153mm
Width	54mm

### Electrical

Mains Frequency	50 Hz
Maximum Wattage	315W
Minimum Wattage	20W
Transformer	Electronic
Voltage	240V