

LED Strip Flexible Tape Ultra Seamless 240 6W 24V

LED Strip Flexible Tape Ultra Seamless IP65 10m (240xSMD 3014 LEDs/m)

24V

60W (6W/m) 2700K Warm White



MR. RESISTOR®
Lighting Specialist Est. 1968



TAPEC240 10M IN

60W (6W/m) 2700K Warm White

Quicklink: Q503B

General

Construction Plastic

Dimmable Yes

IP Rating IP65

LED Chip SMD 3014

LED per Tape 240

Dimensions

Cut Length 25mm

Length 10m

Width 10mm

Electrical

Maximum Wattage 60W (10 x 6W)

Voltage 24V DC

Light Characteristics

Colour Rendering Index 80

Index

Colour Temperature 2700K Warm White

Lumens 5000 lm

Lumens Per Metre 500 lm/m

Lumens Per Watt 83 lm/W

Watts Per Metre 6 W/m

LED Strip Flexible Tape is a versatile light source with a wide range of uses that can be either decorative or functional. It has an IP65 rating making it suitable for bathrooms and kitchens. Easy to install with pre-fitted double-sided backing tape and can be cut to a specific length.

Anything from a short linear run of light for under cabinet or plinth lighting, shelving or back lighting mirrors to large scale applications such as low level lighting in corridors, dropped ceilings, cove lighting, doorways, handrails and staircases can be achieved. A wide range of extrusions and diffusers are available to suit any location and produce different effects.

LED Tape Ultra Seamless carries an IP65 rating making it suitable for bathrooms and kitchens. We would recommend using this tape with our Liger diffusers and 12mm deep channels to achieve a line of light with no dark spots.

This 10 meter LED tape cannot be extended any further. For lengths of more than 10m, you would need to put the extra tape on an additional power cord and position them one after another, wiring the power cords back to the driver in parallel. This LED tape also has a cut mark every 25mm, meaning you can achieve precise lengths for your installation. The maximum distance between the power supply and LED tape is 10 metres. We recommend using 1.5mm² cable. The maximum total length is 20 metres for the LED tape and power supply combined.

This LED tape is dimmable and we recommend using the Triac LED Dimming Driver. Ensure the dimming driver you use exceeds the total wattage of the LED Tape.