



WISEDIM KIT

4 Channel 4 x 700W
Quicklink: QDAB

General

Colour	Grey
IP Rating	IP54

Detection Range	200m
-----------------	------

Dimensions

Depth	100mm
Height	227mm
Width	256mm

Electrical

Maximum Wattage	2800W
Maximum Wattage per Circuit	700W
Minimum Wattage per Circuit	60W
Voltage	240V

The **Wise Dim Leading Edge Kit** is a 2800W 240V dimmer that contains four independent 700W dimmer channels and is controlled by wireless switches. It can dim incandescent, mains halogen and low voltage halogen. Any circuit can be changed from dimming to switching with the use of a dipswitch. This allows non-dimmable fittings such as fluorescents and LEDs to also be operated.

Please note the following:

- It is not recommended for use with dimmable LED and compact fluorescent lamps
- This box cannot be scene programmed
- It is not compatible with WISE INTENSE3 and WISE INTENSE6 transmitter switches

The kit contains all the components required to achieve wireless lighting control; a 4 button remote keyfob and a 7 button wall switch to control the circuits. This product can be programmed in 4 different ways using our wireless switches:

Option A - Dimming Programming

Programming a 1 button switch gives you on/off with a quick press and dimming up and down while holding the switch. Lights will always turn on at the last dimmed level.

Option B - Two Button Switching ON/OFF

Programming a 2 button switch gives you ON and OFF on two separate buttons for one circuit. Please note, programming a circuit in this way will result in the circuit being unable to dim.

Option C - Master ON/OFF

Programming a 2 button switch gives you ON and OFF on two separate buttons for all four circuits. Please note, programming circuits in this way will result in all circuits being unable to dim.

Option D - PIR Sensor

Programming a *Wise PIR Radio Sensor* gives you ON and OFF on one circuit or all four circuits depending on if Option B or Option c is used. Please note, programming circuit(s) in this way will result in all circuits being unable to dim.

Wise Switches / Remotes



The main 4 buttons from our 7 button wireless wall mounted switch will operate the 4 circuits. The other three buttons perform the functions 2 circuits on, 4 circuits on, and all the circuits off. These three buttons allows the user basic scene setting capabilities. Each circuit on the Wise Dim is fused individually with a 3.15 amp fuse to protect all the circuits from overloading.

Wise Controls Introduction Video

