

# Contour

Contour Square 45° Wired Dimming Kit  
Aluminium 2700K Warm White



## LEDSYWD ASWW

Aluminium 2700K Warm White  
Quicklink: Q1DD5

### General

Colour	Aluminium
Construction	Aluminium
Dimmable	Yes
IP Rating	IP54

Maximum 1 Watt LED's	2000mm
----------------------	--------

### Dimensions

Cable Length	2mm
Cut Out	100mm (Diameter)
Length	112mm
Minimum Ceiling Depth	40mm
Vertical Rotation	20°
Width	112mm

### Electrical

Amperage	700mA
Maximum Wattage	27W (3 x 9W)
Minimum Wattage	25000 hrs

### Light Characteristics

Beam Angle	45°
Colour Rendering Index	80
Colour Temperature	2700K Warm White
Lumens	1683 lm
Lumens Per Watt	62 lm/W

The **Contour Square 45° Wired Dimming Kit** consists of 3 x 9W LED downlighters, a 3 way power lead splitter and a resistive dimmable transformer. This gives you the building blocks to have completely dimmable, bright, energy efficient LED lighting.

Each Contour downlight produces 410 lumens, which is comparable with a 35W GU10. This means you can easily change over your current set up from power hungry halogens, to environmentally friendly LEDs by simply swapping the fittings on a one to one basis. This would save you money, without sacrificing overall brightness.

### Ordering extra downlights

If you require more than 3 downlights, then a second Contour Wired Dimming Kit is all you need in order to double your number of fittings to 6. If you need to add 1 or 2 units to your kit, then all you have to do is order 1 x resistive dimming power supply, and 1 or 2 x Contour LED downlight.

Before ordering this kit, please be aware that your dimmer module will have a minimum load which you will have to adhere to. This means that if your dimmer module has a minimum load of 40W then you will need at least 5 LED Contour Downlights to be able to dim smoothly.

# Contour

Contour Square 45° Wired Dimming Kit  
Aluminium 2700K Warm White

---

