

# Wireless Intense Switches

Wise Switch 3 Channel  
Antique Bronze 3V



## WISE INT3 BMA

Antique Bronze 3V  
Quicklink: Q28B0

### General

Colour: Antique Bronze  
Construction: Steel / Plastic  
IP Rating: IP20

Operating Temperature: -10°C ~ +55°C  
Radio Frequency: 868.3 MHz

### Dimensions

Depth: 9mm  
Height: 86mm  
Width: 86mm

### Electrical

Replacement Battery: CR2430  
Voltage: 3V

Wireless switches can be used to control any of the receivers in the Wise Controls range. The function of the switch, and each of its buttons, depends upon the function of the wireless receiver it is programmed to. Therefore a single button can be used for a variety of functions including, but not restricted to, on/off, on/off and dimming, or master off only.

Wise intense switches are surface mounted so can be positioned almost anywhere. They are battery powered and a CR2430 battery is included with each unit. The CR2430 Battery has a life span of 4-5 years.

## Wise Controls Introduction Video

