

Shower

Shower RGB
4W Chrome/Clear



MR. RESISTOR[®]
Lighting Specialist Est. 1968



DH2063RGB CHR

4W Chrome/Clear
Quicklink: Q3020

General

Colour Chrome
Construction Die-Cast Aluminium

Controller Input 24V
Controller Output 350mA
Driver Input 240V
Driver Output 24V

Dimensions

Cut Out 72mm (Diameter)
Diameter 85mm
Minimum Ceiling Depth 100mm

Electrical

Amperage 350mA
Maximum Wattage 4W

The **Shower Light RGB** is a IP55 rated fixed downlight with a plug and play 46° RGB LED Worm.

A Chameleon Master 350mA 21W pack can operate a maximum of five 4W downlights. If more downlights are required a Chameleon Slave pack can be added which can also control a maximum of five 4W downlights. An unlimited number of 21W Chameleon Slave 350mA 21W packs can be used with a Chameleon Master 350mA 21W pack.

Wireless Switches and Remotes

A 7 button wireless wall switch or remote is needed to control the LEDs. Using either the wall switch or remote allows the user to:

- Select one of the 8 preset colours (Red, Green, Blue, Orange, Cyan, Magenta, Yellow)
- Start a smooth colour cycle
- Reverse the colour cycle
- Choose between 3 different colour cycle speeds
- Pause on one of the 1000 different shades of colours available
- Re-program the 8 preset colours with 8 colours of your own choice