



RNR54 MAS4 RGB

16W Bronze Quicklink: Q3053

General

Colour Bronze

Construction Die-Cast Aluminium

IP Rating IP20

Controller Input 24V
Controller Output 350mA
Driver Input 240V
Driver Output 24V

Dimensions

Cut Out 80mm (Diameter)

Diameter 90mm Horizontal Rotation 360° Minimum Ceiling 85mm

Depth

Vertical Rotation 35°

Electrical

Amperage 350mA

Maximum Wattage 16W (4 x 4W)

The **Rock 'n' Roll 50 RGB Master 1** contains all the necessary components to achieve colour change LED lighting.

A Chameleon Master 350mA 21W pack can operate a maximum of five 4W downlights. If more downlights are required a Chameleon Slave pack can be added which can also control a maximum of five 4W downlights. An unlimited number of 21W Chameleon Slave 350mA 21W packs can be used with a Chameleon Master 350mA 21W pack.

Wireless Switches and Remotes

A 7 button remote is included to control the LEDs. This allows the user to:

- Select one of the 8 preset colours (Red, Green, Blue, Orange, Cyan, Magenta, Yellow
- Start a smooth colour cycle
- Reverse the colour cycle
- Choose between 3 different colour cycle speeds
- Pause on one of the 1000 different shades of colours available
- Re-program the 8 preset colours with 8 colours of your own choice