



## AL4020KIT MASTER1

3W RGB

Quicklink: Q30AF

### General

Colour	White
Construction	Aluminium
Dimmable	Yes
IP Rating	IP65

Dimmable Yes

### Dimensions

Burial Tube Cut Out	60mm
Depth	35mm
Length	70mm
Plate Depth	2mm
Tube Length	73mm
Width	70mm

### Electrical

Amperage	350mA
Maximum Wattage	3W

The **Pierrot RGB Master** contains a 3W fitting that is ideal for use in all areas which require a little something different. From homes and bars, to bathrooms and outside, this really is a universal fitting. The kit includes a colour change regulator pack, a 24V power supply, end cap, power cord and couplers. The system is also completely plug and play meaning that installation is easier and simpler than ever.

A Chameleon Master 350mA 21W pack can operate a maximum of six 3W Pierrot's. If more 3W Pierrot's are required a Chameleon Slave pack can be added which can also control a maximum of six 3W Pierrot's. An unlimited number of 21W Chameleon Slave 350mA 21W packs can be used with a Chameleon Master 350mA 21W pack.

A **wireless remote** is included to control the LEDs. This allows the user to:

- Select one of the 8 preset colours (Red, Green, Blue, Orange, Cyan, Magenta, Yellow)
- Start a smooth colour cycle
- Reverse the colour cycle
- Choose between 3 different colour cycle speeds
- Pause on one of the 1000 different shades of colours available
- Re-program the 8 preset colours with 8 colours of your own choice