



### **WISE DUSW**

2 Channel White Quicklink: Q36FA

### General

Colour White
Construction Plastic
IP Rating IP54

Photocell Range 10 lux to 300 lux Time Delay 2 hrs to 16 hrs

## **Dimensions**

Depth 37mm Length 75mm Width 60mm

### Electrical

Input Voltage 240V Maximum Wattage 1500W Output Voltage 240V The Wired PIR Sensor Kit 240V is a Wise Transmitter with a wired Twilight PIR Switch

. The Wise Transmitter enables the PIR to send wireless signals to any Wise Receiver. Ideal for when you cannot install any cables between your sensor and your lighting circuit.

The transmitter is small enough to be placed in many locations, for example, in the ceiling, in the wall either through it, behind a recessed light fitting or in a surfaced mounted fitting. The transmitter should be placed in a suitable insulated box.

It can be fitted into a small waterproof box to allowed it to be used outside for your garden lighting, garage doors and water features.

The transmitters are designed to be simple to install, easy to use and most importantly, reliable.

# Wise Controls Introduction Video

