

FSTWIFIU

13A White Quicklink: Q4F7E

General

Colour White Construction Plastic

Dimensions

Depth 38mm Height 85mm Width 85mm

Electrical

Voltage 240V

The FSTWiFi 13A Fused Spur enables wifi control for all manner of electrical applications.

Ideal for switching lighting and electrical heaters. Programme settings are all activated via your mobile device, giving you access to control your installation at any time, no matter where you are. Total 13A 3kW control with confirmation of settings and switching status of the connected appliance via the on-screen app.

Energy saving control at your fingertips!

App Features:

- Available for Android and IOS only.
- Works with WiFi and 4G.
- Can reduce running costs if unwanted programmes are cancelled.
- Supports multiple devices.
- Supports multiple users.
- Auto mode, with permanent ON, permanent OFF and holiday modes.
- Optional 1 and 2 hour boost.
- Advance function.
- Supports additional programme sets, for half terms, holidays and seasonal programmes.
- 6 ON/OFF periods, with daily repeats.
- Positive ON/OFF status, with colour coded display.
- Graphic representation and summary of output.
- Automatic summer/winter changeover.

Technical Ratings:

- Operating voltage 230V 50Hz.
- 13A rated suitable for 3kW: Immersion heaters, 5A inductive load, 1000W tungsten, 500W LED, 100W CFL and 500W Fluorescent.
- Manual override.
- Replaceable 13 Amp BS1362 fuse.
- Fits standard 25mm deep single wall box.
- Direct retrofit for BS1363 fused connection unit.
- Double pole isolating switch.
- Operating temperature 0 40°C.