## LED Tape Ultra Seamless 240 6W 24V

LED Tape Ultra Seamless 10m (240xSMD 3014 LEDs/m) 24V 60W (1m=6W) 3000K Warm White



## **TAPEC240 10M WW**

60W (1m=6W) 3000K Warm White Quicklink: Q503C

## General

Construction Dimmable IP Rating	Plastic Yes IP65
LED Chip LED per Tape	SMD 3014 240
<b>Dimensions</b> Cut Length Length Width	25mm 10m 10mm
<b>Electrical</b> Maximum Wattage Voltage	60W (10 x 6W) 24V DC
<b>Light Characteristics</b> Colour Rendering 80 Index	

IndexColour Temperature3000K Warm WhiteLumens5000 lmLumens Per Metre500 lm/mLumens Per Watt83 lm/WWatts Per Metre6 W/m

LED Tape is a versatile light source with a wide range of uses that can be either decorative or functional. Easy to install with pre-fitted double-sided backing tape and can be cut to a specific length.

Anything from a short linear run of light for under cabinet or plinth lighting, shelving or back lighting mirrors to large scale applications such as low level lighting in corridors, dropped ceilings, cove lighting, doorways, handrails and staircases can be achieved. A wide range of extrusions and diffusers are available to suit any location and produce different effects.

LED Tape Ultra Seamless carries an IP65 rating making it suitable for bathrooms and kitchens. We would recommend using this tape with our Liger diffusers and 12mm deep channels to achieve a line of light with no dark spots.

This 10 meter LED tape cannot be extended any further. For lengths of more than 10m, you would need to put the extra tape on an additional power cord and position them one after another, wiring the power cords back to the driver in parallel. This LED tape also has a cut mark every 25mm, meaning you can achieve precise lengths for your installation. The maximum distance between the power supply and LED tape is 10 metres. We recommend using 1.5mm<sup>2</sup> cable. The maximum total length is 20 metres for the LED tape and power supply combined.

This LED tape is dimmable and we recommend using the Triac LED Dimming Driver. Ensure the dimming driver you use exceeds the total wattage of the LED Tape.