



### CCRGB LAMP GX5.3

RGB 30°

Quicklink: QE8F

#### General

|              |                 |
|--------------|-----------------|
| Cap          | GU5.3 / MR16    |
| Construction | Metal / Plastic |

#### Dimensions

|          |      |
|----------|------|
| Diameter | 50mm |
| Length   | 52mm |

#### Electrical

|                 |          |
|-----------------|----------|
| Maximum Wattage | 5W       |
| Transformer     | Required |
| Voltage         | 12V DC   |

#### Light Characteristics

|            |     |
|------------|-----|
| Beam Angle | 30° |
| Lux At 1m  | 86  |

This retrofitted **Happy LED Colour Changing Lamp** is able to be fitted instead of a halogen dichroic lamp. This means that it is possible to fit it in most 50mm low voltage light fittings. The colour changing is operated by an IR remote. This means that the remote must be pointed at the lamp itself in order for colour changing to work.

**Please note:** Only one CCRGB remote is required to control all of the fittings. The remote does not change every fitting simultaneously, it is required that you set each fitting to your desired setting individually.

There are 16 different colours available, each with four different levels of brightness. There are also four colour changing programs available, Flashing (fast flashing colour changing), Strobe (slow strobe colour changing), Fade (fast fading colour changing), and Smooth (slow smooth colour changing). Providing that the lamp was on a constant colour before switch off from the remote, the lamp memory will ensure that at turn on the same colour is produced.