

Wireless Style Time Clock

Wise Style Time Clock
2 Channel White



WISETC4 WHITE

2 Channel White
Quicklink: Q11F0

General

Colour White

Operating Temperature -10°C ~ +55°C

Radio Frequency 868.3 MHz

Dimensions

Depth 13mm

Height 86mm

Width 86mm

Electrical

Power Supply 3V Lithium Battery CR2032


The **Wise Style Time Clock** switch can be programmed to any of our **Wise** receivers, a maximum of two receivers per switch. Examples include the **Wise Box**, **Wise Dim Box**, **Wise Pack Switch Receiver**, **Wise Switch receiver** and any **Wise Scene Receiver** (if a separate master on and master off is programmed). This product is ideal for use in scenarios where lighting is required to turn on regularly without any user input once set up. A maximum of six commands a day, 7 days a week can be programmed. Alternatively, you can use the built-in functions to control your lighting, such as automatic dusk to dawn mode. Please refer to the instructions located on the downloads tab for more information.

The battery life lasts up to 2 years.

Key Benefits

- The timeclock can control two circuits manually as well as control them automatically once timer functions are set up
- Can set automatic ON when the sun sets and OFF for a specific time e.g. 11pm
- It allows the possibility of programming 6 commands per day, 7 days a week
- Commands can be automatically programmed for dusk and dawn, every day of the week and random start
- Radio switches require no wiring
- No back box required

Wise Controls Introduction Video



Wise Timeclock Programming Video

Wireless Style Time Clock

Wise Style Time Clock
2 Channel White

