

# Trapeze

Wire Adjustable Spot 12V  
Chrome 35W

---



## MR129 CHROME

Chrome 35W  
Quicklink: Q17BD

---

### General

Cap	GU5.3 / MR16
Colour	Chrome
Construction	Stainless Steel
Dimmable	Yes
IP Rating	IP00

### Dimensions

Height	120mm
Width	90mm

### Electrical

Maximum Wattage	35W
Voltage	12V

The **Wire Adjustable Spot** is an adjustable stainless steel single arm spot fitting.

This product must be purchased with the following *Trapeze Accessories*; *PVC Coated Wire Cable*, *Wire Tensioners* and a *Wire Transformer*. Other accessories are also available depending on the track layout you desire. For ideas and required components, please see pages 6 and 7 of our *Trapeze System Catalogue* located in the downloads tab and the *Trapeze Accessories* section.

The *Trapeze Wire System* can be run to a maximum length of 6 metres with a maximum wattage of 300W. When connecting this fitting on the cable it is important that the P.V.C. outer casing is pierced in order to make a solid connection.

A solid core cable must be used to connect power from the *Wire Transformer* to the *Wire Tensioner*, the *PVC Coated Wire Cable* must not be used for this purpose. Alternatively, as long as the single strands of the transformer cable are bundled together tightly into one piece and soldered if possible, it can be connected to the *PVC Coated Wire Cable* via a *Wire Floating Live End* or more directly via the *Wire Tensioner*.

For further detail on connecting all cables to the *Wire Tensioners*, please see the technical tab.

---