



### **RLED36-3DCI**

3 x 12W LED RGB  
Quicklink: Q218A

#### **General**

Construction	Plastic
IP Rating	IP00

Radio Frequency	433.9MHz
-----------------	----------

#### **Electrical**

Maximum Wattage	36W (3 x 12W)
-----------------	---------------

The **RAKO Constant Current Dimming Driver** is a wireless three channel (RGB) 36W constant current dimming LED driver. Up to 12 LED can be connected in series to a maximum of 12W on each channel. The maximum current settings are selectable from 350mA, 500mA, 600mA and 700mA. The unit requires up to 48V 36W DC power supply (RAKO RAPSU48-36).