

**28503150/10D W/W**3000K Warm White 10°
Quicklink: Q24F2**General**

Colour	White
Dimmable	Yes
IP Rating	IP00

Dimmable Yes

Dimensions

Cut Out	23mm (Diameter)
Depth	16mm
Diameter	25mm

Electrical

Amperage	350mA
Maximum Wattage	1W

Light Characteristics

Beam Angle 10°

The **Focus LED 1 Watt** is a very small versatile unit. It can be used separately or together with a light fitting. It has a 21mm cut out.

This LED has a plastic bezel which is available with a 10° or 30° angle of light in cool or warm white.

Many different LED power supplies are available that allow you to achieve more with your lighting. Simply select the correct wattage depending on how many total LED fittings it will be connected to.

LED Driver Options

- LED Driver (Switching) - Use this driver for on/off control. Cannot be used for dimming.
- LED Driver (Dimming) - For use with nearly all domestic dimming lighting. Most resistive dimmers have a minimum load of 60W, therefore ensure that if this not met, a dummy load is added to the circuit, such as a mains voltage halogen fitting.
- LED Driver (1-10V) - For use with 1-10V dimmer modules or 1-10V control systems. This type of dimming does not have a minimum load.
- Wise Chameleon (Dimming + Wireless) - This controller can be used for both switching and dimming. Additionally, this unit can communicate via radio and external push buttons, allowing you to wirelessly control your fitting. Note that an additional 24V LED driver is required to power the Wise Chameleon pack.